



# VKD233HB Datasheet

1ch Touch/One-to-one output

Rev.1.2

## Intellectual Property Statement:

Shenzhen Vinka Microelectronics Co., Ltd. (hereinafter referred to as “the Company”) owns legally registered intellectual property rights in both domestic and international jurisdictions. Any unauthorized use of the Company’s products or patented technologies by individuals or organizations is strictly prohibited.

The Company reserves the right to take legal action against any infringement, and to seek full compensation for damages or unlawful gains.

The Company’s name and trademarks are legally protected and may not be used or imitated without explicit written permission. No implied or express license shall be granted under any circumstances.

## 1 General Description

VKD233HB is a single-channel touch detection chip. Its low power consumption, wide operating voltage range and stable touch detection effect can widely meet the needs of different applications. This touch detection chip is specially designed to replace traditional keys. It is equipped with a built-in voltage stabilizing circuit to provide a stable voltage for the touch detection circuit to use. The size of the touch detection PAD can be designed within a reasonable range according to different sensitivities.

## 2 Key Features

- Operating voltage: 2.4V to 5.5V
- Operating current 4.0uA@VDD=3.0V  
Standby current 1.5uA@VDD=3.0V
- Low-voltage reset function (LVR)
- Built-in dedicated voltage stabilizing circuit for touch detection
- The response time is approximately 46ms @VDD=3V
- The sensitivity can be adjusted by an external capacitor (1 to 60pF)
- Built-in key debouncing, no need for external software to debouncing
- Touch without leaving and keep outputting
- Pin Q is the CMOS output  
The output level is selected by the MHL pin as either high level valid or low level valid  
The output mode is selected by the MDT pin as either direct output or latch output
- There is approximately 0.3 seconds of stabilization time after power-on. During this period, all functions are disabled. Do not touch the detection point during this time
- Self-calibrate parameters according to environmental changes
- The static electricity of HBM is greater than 4KV
- Available Packages:  
SOT23-6L(3mm x 3mm PP=0.95mm)


### 3 Product Selection

Part No.	Working voltage	Mode working/standby	Output (/ Optional)	Packaging
VKD223EB	2.0-5.5V	4.0uA/1.5uA(3V)	Directly/latch high/low levels	SOT23-6L
VKD233HB	2.4-5.5V	4.0uA/1.5uA(3V)	Directly/latch high/low levels	SOT23-6L
VKD233HH	2.4-5.5V	4.0uA/1.5uA(3V)	Directly/latch high/low levels and hold for 16 seconds to reset	SOT23-6L
VKD233HS	2.4-5.5V	4.0uA/no(3V)	Directly/latch high/low levels and hold for 16 seconds to reset	DFN6L
VKD233HR	2.4-5.5V	4.0uA/1.5uA(3V)	Directly/latch high/low levels and hold for 16 seconds to reset	DFN6L
VKD233HM	2.4-5.5V	5.0uA/no(3V)	Direct/latch open leakage low valid press and hold for 16 seconds to reset	SOT23-6L
VKD101HH	2.4-5.5V	4.0μA/1.5μA(3V)	Directly/latch high/low levels	SOT23-6L

### 4 Ordering Information

Part No.	Packaging	Tube Qty	Tray(reel) Qty	Box Qty	Total Qty	Notes
VKD223EB	SOT23-6L	—	3000/reel	30000/box	120000 PCS	
VKD233HB	SOT23-6L	—	3000/reel	30000/box	120000 PCS	
VKD233HH	SOT23-6L	—	3000/reel	30000/box	120000 PCS	
VKD233HS	DFN6L	—	3000/reel	30000/box	120000 PCS	
VKD233HR	DFN6L	—	3000/reel	30000/box	120000 PCS	
VKD233HM	SOT23-6L	—	3000/reel	30000/box	120000 PCS	
VKD101HH	SOT23-6L	—	3000/reel	30000/box	120000 PCS	

## 5 Package Pinout Information(SOT23-6)



For more information: [Page 10](#)


## 5.1 VKD233HB/SOT23-6L Pin Description

Pin No.	Pin name	I/O	Function Description
1	Q	O	CMOS Output
2	GND	P	Negative power supply
3	TP	I/O	Touch detection
4	MHL	I—RL	Select the effective output level: 0(default)- High level valid; 1- Low level effective
5	VDD	P	Positive power supply
6	MDT	I—RL	Select the output mode 0(default)→Direct output ; 1→Latch output

- I CMOS Input
- O CMOS Output
- I/O CMOS Input/Output
- P Power supply/Groundin
- I-RH CMOS input has a built-in pull-up resistor
- I-RL CMOS input has a built-in pull-down resistor
- OD Open-drain output, no diode protection circuit

## 6 Functional Description

### 6.1 Block Diagram



## 6.2 Output Mode (selected using pins MDT and MHL)

MDT: Choose direct output or latch output.

MHL: Select whether the output is high level effective or low level effective.

Q Pin output parameters :


MDT	MHL	Output parameters
0	0	Direct CMOS output, high level effective
0	1	Direct CMOS output, low level effective
1	0	Latched CMOS output, power-on state = 0
1	1	Latched CMOS output, power-on state = 1

Notes: Considering energy conservation and packaging, the MDT/MHL pins are designed as latch types at the beginning of power-on. The status is 0 or 1; If the MDT/MHL pin is connected to VDD or GND, the state will become 1 or 0 and will not occur Current leakage.

Output option pin	The initial state after power-on
MDT	0
MHL	0

## 6.3 Operating Modes

The VKD233HB can save energy when operating in standby mode. After detecting a key touch in this mode, it will switch to working mode until the key touch is released and hold for about 10 seconds before returning to standby mode.



## 6.4 Sensitivity Adjustment

The size of the detection PAD connected on the PCB and the total load of the capacitors (parasitic capacitance and Cs capacitance) will affect the sensitivity. The degree and sensitivity adjustment need to be adjusted according to the actual application.

The following provides some methods for externally adjusting the sensitivity:

1. Adjust the size of the detection PAD


Under the condition that other factors remain unchanged, using a larger detection PAD size can increase the sensitivity, and vice versa. It will reduce the sensitivity, but the detection of PAD size must be used within the effective range.

2. Adjust the thickness of the medium (shell)

Under the condition that other factors remain unchanged, using a thinner medium can increase sensitivity; conversely, it will reduce sensitivity. Sensitivity, but the thickness of the medium must be below the maximum limit value.


3. Adjust the Cs capacitance value (please refer to the following figure)

Under the condition that other factors remain unchanged, it is sensitive if the Cs capacitor is not connected to GND on the touch PAD. The degree is the most sensitive. The Cs capacitance is within the usable range ( $1 \leq C_s \leq 60\text{pF}$ ), and the larger the Cs capacitance value, the more sensitive it is. The lower the sensitivity.



## 7 Application Circuits

It is recommended to use an LDO for power supply




The output mode is determined by the states of the MHL pin and the MDT pin

**MDT MHL**

NC	NC	Direct CMOS output, high level effective
NC	VDD	Direct CMOS output, low level effective
VDD	NC	CMOS latch output, power-on output 0
VDD	VDD	CMOS latch output, power-on output 1

A 1K resistor is connected in series with the touch foot to enhance anti-interference. The commonly used value is 470R to 1K, with a maximum of no more than 10K. Depending on the interference situation, the resistance value should be increased if the interference is severe

C0 is used to fine-tune the sensitivity of each channel. Generally, the larger the capacitance ranging from 1pF to 60pF, the less sensitive it is. For conventional applications, it can be left unconnected



### Notes:

1. On the PCB, the wire length from the touch PAD to the touch foot should be as short as possible, and the touch trace must not be parallel or cross with other wires.
2. The power supply must be stable. Fluctuations, rapid drifts or interference in the supply voltage may cause abnormal sensitivity or false detection.
3. The boards covering the PCB must not contain metals or conductive materials, and the same applies to surface coatings.
4. C1 capacitor must be used between VDD and GND, and the distance between it and the VDD and GND pins of the chip should be the shortest. The resistor R2 on the power supply. It is recommended to add capacitor C2.
5. Adjust the sensitivity with capacitor C0(0-60pF). The smaller the capacitor value, the more sensitive it is. The sensitivity is the highest when no capacitor is connected. Sensitivity adjustment is essential. The adjustment should be made based on the actual application of the PCB. For regular applications, it can be omitted. The C0 must be selected with a smaller temperature coefficient and greater stability Fixed capacitors, such as X7R, NPO.
6. The resistor R0 is mainly used to effectively prevent radio frequency interference and enhance anti-static capability. Its common values range from 470R to 1K, with a maximum not exceeding 10K, Regular applications can be left unconnected.

## 8 Electrical Characteristics

### Absolute Maximum Ratings


Parameter	Symbol	Ratings	Unit
Power voltage	VDD	-0.3~6.0	V
Input Voltage	V <sub>IN</sub>	GND-0.3~VDD+0.3	V
Storage Temperature	T <sub>STG</sub>	-50~+125	°C
Operating Temperature	T <sub>OTG</sub>	-40~+85	°C
Human Body Mode	ESD	≧4	KV

### DC/AC: (Test condition: Room temperature 25 °C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Test Conditions (25 °C)	
						VDD	Conditions
Operating voltage	VDD	2.4	3.0	5.5	V	—	—
Internal voltage regulator	VREG	2.2	2.3	2.4	V	—	—
Operating current	I <sub>OP</sub>	—	4.0	8.0	—	3.0V	Operating mode
Standby current	I <sub>ST</sub>	—	1.5	3.0	—	3.0V	Standby mode
Output Sink Current	I <sub>IL</sub>	—	8	—	mA	3.0V	V <sub>OL</sub> =0.6V
		—	16	—		5.0V	
Output Source Current	I <sub>OL</sub>	—	-4	—	mA	3.0V	V <sub>OH</sub> =2.4V
		—	-8	—		5.0V	V <sub>OH</sub> =4.4V
Input Low Voltage	V <sub>IL</sub>	—	—	0.2	VDD	VDD	Input Low Voltage
Input High Voltage	V <sub>IH</sub>	0.8	—	1	VDD	VDD	Input High Voltage
Input pull-low resistor	R <sub>L</sub>	—	25k	—	ohm	3.0V	VDD=3V
Output Response Time	T <sub>R</sub>	—	46	—	mS	3.0V	Operating mode
		—	46	—		5.0V	Operating mode
		—	160	—	mS	3.0V	Standby mode
		—	160	—		5.0V	Standby mode

## 9 Package Information

### 9.1 SOT23-6L(3mm x 3mm PP=0.95mm)



MILLIMETER			
SYMBOL	MIN	NOM	MAX
A	2.72	2.92	3.12
A1	0.90	0.95	1.00
A2	0.30	0.35	0.40
B	1.40	1.60	1.80
B1	2.60	2.80	3.00
B2	0.12	0.128	0.135
C	1.00	1.10	1.20
C1	0.04	-	0.10
C2	0.60	0.65	0.70
D	0.03	0.08	0.13
D1	0.30	-	0.60
D2	0.25TYP		
D3	0.60	0.65	0.70

## 10 Disclaimer

**Warranty and liability** — The information provided in this document is believed to be accurate and reliable. However, Shenzhen Vinka Microelectronics Co., Ltd. (hereinafter “the Company”) makes no warranties, express or implied, as to the completeness or suitability of this information for any specific purpose.

In no event shall the Company be liable for any indirect, incidental, or consequential damages, including but not limited to loss of profits, equipment damage, or system failure, arising out of the use of this product or documentation, regardless of the legal theory under which such liability is asserted.

**Right to change** — The Company reserves the right to modify any information contained herein without prior notice. The latest version of this document is available at:

<https://www.szvinka.com/>

**Applicability** — This product is not designed or intended for use in life-critical, medical, or safety systems where failure could result in injury or death. The customer shall assume full responsibility for any such use.

**Application** — All product application descriptions provided herein are intended for illustrative purposes only. The Company makes no representations or warranties, express or implied, regarding the suitability of any specific application without further testing or modification.

The customer is solely responsible for determining whether the Company’s products are appropriate for their intended applications or end customers.

The customer shall ensure proper design practices, implementation safeguards, and operational validation to minimize risks associated with product use.

The Company shall not be held liable for any defects, losses, costs, or damages arising from weaknesses or failures in the customer’s own products or applications, or from the integration or use of third-party products.

Furthermore, the customer shall conduct all necessary testing and validation for any third-party deployment of the Company’s products to avoid potential misuse or associated damages. The Company assumes no liability in this regard.

**Commercial terms of sale** — Unless otherwise agreed in writing, sales of this product are subject to the Company’s standard terms and conditions of sale. The Company expressly rejects the applicability of the customer’s general terms and conditions.

**Export control** — This product may be subject to applicable export control regulations. The customer is solely responsible for compliance with such regulations, including obtaining any necessary export licenses.

## 11 Revision History

No.	Version	Date	Modify the content	Check
1	1.0	2018-08-10	Original version	YES
2	1.1	2020-02-11	Add reference circuit	YES
3	1.2	2025-11-13	Update version	YES

[1] Consult the recently published documents before starting or finishing the design.

[2] Since the release of this document , the device product status described in this document may have changed and may differ in several cases. The latest product status information can be found on the Internet at <https://www.szvinka.com/>